

FPD2-80-110-30-S

2-Way, 0.08~0.11GHz

Features:

- * Small Size
- * Low Insertion Loss

Applications:

- * Amplifiers
- * Mixers
- * Antennas
- * Laboratory Test

Electrical

Frequency:	0.08~0.11GHz
Insertion Loss:	0.4dB max.
Input VSWR:	1.2 max.
Output VSWR:	1.2 max.
Isolation:	20dB min.
Amplitude Balance:	0.2dB max.
Phase Balance:	$\pm 2^\circ$
Impedance:	50 Ω
Power @SUM Port:	30W max. as divider 2W max. as combiner

Mechanical


Size ^{*1} :	108*70*10mm 4.252*2.756*0.394in
Weight:	165g
Connectors:	SMA Female
Mounting:	4- Φ 3.4mm through-hole

[1] Exclude connectors.

Environmental

Operation Temperature:	-45~+85°C
------------------------	-----------

Outline Drawings



Unit: mm [in]

Tolerance: ± 0.5 mm [± 0.02 in]

How To Order

FPD2-80-110-30-S

Customization is available upon request.