

FSDC-1000-4000-50-20-S

1~4GHz, 50W, 20dB

Features:

- * Broadband
- * Low Insertion Loss

Applications:

- * Amplifiers
- * Transmitter
- * Laboratory Test
- * Radar

Electrical


| | |
|-----------------|------------|
| Frequency: | 1~4GHz |
| Insertion Loss: | 0.5dB max. |
| Coupling: | 20±1dB |
| Directivity: | 18dB min. |
| VSWR: | 1.3 max. |
| Average Power: | 50W |
| Impedance: | 50Ω |

Mechanical

| | |
|----------------------|--|
| Size ^{*1} : | 73*15*11mm 2.874*0.591*0.433in |
| Connectors: | SMA Female |
| Mounting: | 4-Φ2.3mm through-hole 4-M2, depth 5mm |

[1] Exclude connectors and terminations.

Outline Drawings



Unit: mm [in]

Tolerance: ±0.3mm [±0.012in]

How To Order

FSDC-1000-4000-50-20-S

Customization is available upon request.